



## Features

- Open voice door answering with door release
- Adjustable communication volume
- · Automatically turns off in 20 seconds
- Batteries or 6V DC power supply (1 per master)
- . Any LE or LS Series door station can be used to replace the C-D
- . LE-D is physically identical to C-D
- · Second inside room station (separate power supply required)

## C-ML/A C-D EL-128 Ε Ε SKK-620B PT-1210N

## **Unit Dimensions**





## **Specifications**

Power Source 6V DC - Use SKK-620B or 4 'C' Batteries

Communication Door calls in with 2-tone chime, not adjustable,

push TALK button to reply, release-to-listen,

power automatically shuts off circuit

Door Release Contact rating: 50V AC @ 1A

Wiring Door to master: 2-cond., overall shield

Between masters: 2-cond., overall shield

Door to farthest master: 245'(22AWG) 490'(18AWG) Distance

Wire Type Aiphone #822202 or Aiphone #821802